EcoLite™
Leader in LED Lighting

EQUINOX EXIT FLOOD COMBO R
SPECIFICATION SHEET
ECO-LS-ES007SR

Equinox Exit Flood Combo R LED Exit Sign Light I

ECO-LS-ES007SR
120-277



KEY SPECS

POWER

5W

Rated output

Equinox Exit Flood Combo R is a self-contained emergency exit sign with a die-cast housing and snap-on EXIT faceplate, available with red or green LED illumination. Twelve high-output LEDs provide uniform legend visibility, while an integrated 3.6V 800mAh lead-acid battery delivers over 90 minutes of emergency runtime after a 24-hour recharge. The dual-voltage 120/277 VAC input accepts standard line wiring, and knockout patterns on the back plate support junction-box mounting in ceiling, wall, or back-mount configurations. Backed by EcoLite's 10-year non-prorated warranty.

- Commercial & retail buildings
- Offices & corridors
- Schools & institutional facilities
- Healthcare & hospitality

FEATURES

01 Red or green LED EXIT legend
02 Integrated 3.6V / 800mAh lead-acid battery backup
03 >90 minute emergency runtime
04 24-hour full recharge
05 Dual-voltage 120/277 VAC input
06 Ceiling, wall, and back-mount installation



UNIVERSAL
120/277 VAC

BATTERY BACKUP
>90 MIN

DUAL COLOR
RED OR GREEN

01 ORDER INFORMATION

SKU / MODEL	SIZE	WATTAGE	CCT	VOLTAGE
ECO-LS-ES007SR	16.93 × 7.36 in	5 W	—	120-277

02 ELECTRICAL CHARACTERISTICS

SPECIFICATION	5 W
Wattage	5 W
Input Current	0.04 A
Power Factor	0.86 PF
Output Wattage	1–2 W
Recharge Time	24 hr
Emergency Duration	>90 min
Battery	3.6 V / 800 mAh lead-acid
LED Source	12 × red LED
Product Size	430 × 187 × 45 mm

03 DIMENSIONS

MODEL	LENGTH	WIDTH	HEIGHT
ECO-LS-ES007SR	16.93” / 430 mm	7.36” / 187 mm	1.77” / 45 mm

Rectangular footprint · Dimensions ±0.2” · inches [mm]

04 SAFETY WARNING

⚠ READ BEFORE INSTALLATION

1. Installation must be performed by a qualified, licensed electrician in accordance with all applicable national and local electrical codes.