EcoLite™
Leader in LED Lighting

EQUINOX EXIT FLOOD COMBO-SQ
SPECIFICATION SHEET
ECO-LS-ES082A

Equinox Exit Flood Combo-SQ LED Exit Sign Light I

ECO-LS-ES082A
120-277



KEY SPECS

POWER

4W

Rated output

Equinox Exit Flood Combo-SQ is a combination LED exit sign and emergency light built into a single low-profile housing for code-compliant egress lighting. The unit features ultra-bright LED illumination, an integrated 3.6 V / 600 mAh sealed lead-acid battery providing over 90 minutes of emergency runtime, and a 24-hour recharge cycle. Dual-voltage 120/277 V input wiring supports universal installation, and a built-in test switch verifies battery function. The fixture mounts to walls or ceilings using the supplied plate and hardware. Backed by EcoLite's 10-year non-prorated warranty.

- Commercial & office buildings
- Retail & hospitality spaces
- Schools & institutional facilities
- Stairwells & egress corridors

FEATURES

01 Combination exit sign and emergency light
02 Ultra-bright LED light source
03 Integrated 3.6 V / 600 mAh lead-acid battery
04 >90 min emergency runtime
05 24-hour battery recharge
06 Dual 120/277 V input



DUAL VOLTAGE
120/277V

EMERGENCY
>90 MIN

RECHARGE
24 HR

01 ORDER INFORMATION

SKU / MODEL	SIZE	WATTAGE	CCT	VOLTAGE
ECO-LS-ES082A	11.02 × 4.56 × 2.67 in	4 W	—	120-277

02 ELECTRICAL CHARACTERISTICS

SPECIFICATION	4 W
Size	11.02 × 4.56 × 2.67 in
Wattage	4 W
Input Current	0.03 A
Power Factor	0.97
Output Wattage	2 × 2 W
LED Source	Ultra-bright LED
Battery	3.6 V / 600 mAh sealed lead-acid
Recharge Time	24 hr
Emergency Duration	>90 min
Input Voltage	120 / 277 VAC

03 DIMENSIONS

MODEL	LENGTH	WIDTH	HEIGHT
ECO-LS-ES082A	11.02" / 280 mm	4.56" / 116 mm	2.67" / 68 mm

Rectangular footprint · Dimensions ±0.2" · inches [mm]

04 SAFETY WARNING

⚠ READ BEFORE INSTALLATION

1. Installation must be performed by a qualified, licensed electrician in accordance with all applicable national and local electrical codes.